

Instructions for configuring the system

[Installer's part of the system](#)

[User's part of the mobile system](#)

Instructions for the system installer

- Make sure you have the required minimum versions installed on 21553.1 and 01945.
Caution: If there is more than one 21553.1 (Multimedia 10) in the system, only one of them must be configured as "**Primary**". Any other 21553.1 in the system must be connected to the WebServer as "**Secondary**". . In addition, the Multimedia 10 configured as "**Primary**" must coincide with the **Master Entryphone**
Set a static IP on Multimedia 10, then run a **Search WSV**
- Add the system's entrance panels and any 69AM (4 camera modules) to the 21553.1. This is done via **Settings** (log in as installer), on the page for **Video intercom – VoIP**
- Log in via a browser to the 01954 (Vimar WebServer) and go to the page for **General settings**.
If the above steps are completed successfully, you will see the "**Video intercom**" menu and you can continue with the following steps
- Add the enabled mobile devices to the page for **General settings - Video intercom - Telephones**






Telephones

- Add the new devices using the "+" button




- Press the "edit" button and pair the device with a **Number** (VoIP ID) and a **Password**
Number (ID VoIP) and **Password** accept alphanumeric values. At least one character is required for each of the two credentials



- Add the mobile devices you have just created to a **Call groups** on the page for **General settings - Video intercom - Call groups**.
Create other new **Call groups** , as preferred, pairing them with one or more mobile devices



Video Intercom



Call Groups

- By using the “**Edit**” button and then the “+” button you can drag the mobile devices into the group
- Pair each entrance panel in the system with a **Call group** on the page for **General settings - Video intercom – Video Intercom**



Video Intercom



Video Intercom

- Press the “**Edit**” button and pair the relevant entrance panel with a **Call group**


Instructions for the mobile device user

- Add a **System name**

For example: Beach House

- Enter the **IP Address of the Multimedia 10**

It is located on the "System info" page of the Settings for Multimedia 10 under the heading **IP Address**



- Enter the **ID VoIP** and the **Password** for the mobile device being used

This information must have previously been added by the installer using the procedure described above